



**PROJECT DESIGN DOCUMENT FORM
FOR SMALL-SCALE CDM PROJECT ACTIVITIES (F-CDM-SSC-PDD)
Version 04.1**

PROJECT DESIGN DOCUMENT (PDD)

Title of the project activity	Hapugastenne and Hulu Ganga Small Hydropower Projects
Version number of the PDD	04
Completion date of the PDD	27/11/2013
Project participant(s)	<ol style="list-style-type: none">1. Eco Power (Private) Limited (EPL)2. International Finance Corporation as Trustee of the IFC-Netherlands Carbon Facility (INCaF)3. Netherlands' Ministry of Infrastructure and the Environment (IenM)
Host Party(ies)	Sri Lanka (Host)
Sectoral scope(s) and selected methodology(ies)	Sectoral Scope 1: Energy Industries (renewable/non renewable sources) AMS-I.D. – Renewable electricity generation for a grid, Version 05
Estimated amount of annual average GHG emission reductions	49,796 tCO ₂ e

SECTION A. Description of project activity

A.1. Purpose and general description of project activity

>>

This PDD presents a bundle of four (4) small-scale, run-of-river hydropower plants in Sri Lanka. The four plants represent four distinct investment projects at different locations and with start dates spanning a five year period. The rationale for grouping of the projects in one PDD is based on the fact that one company will build, own and operate all four facilities.

The four hydropower plants, which range in size from 2.526 MW to 5.052 MW, have a combined capacity of 13.568 MW.

Power Plant	Capacity (in MW)
Hapugatenne I	5.052
Hapugastenne II	2.526
Hulu Ganga I	3.000
Hulu Ganga II	2.990
Total Capacity	13.568

The electricity from each of the hydropower plants will be sold to the monopoly government-owned utility in Sri Lanka, the Ceylon Electricity Board (CEB), through a standard power purchase agreement available to all renewable energy based power generators under 10 MW, including small hydropower. The CEB pays producers of renewable energy an amount (adjusted annually) based on short run avoided energy costs of operating thermal power stations. The payment is based on actual electricity generated by the small hydropower facilities and does not include a capacity charge. Currently, the marginal thermal power plants operate on fuel oil or diesel and the share of thermal power in Sri Lanka is expected to increase dramatically over the next ten years. The small hydropower projects do not figure in the CEB expansion plan, nor are they factored into the annual electricity supply-demand forecasts. Operation of these small hydropower plants will result in a displacement of electricity from the highest marginal cost thermal power stations.

The projects will result in a reduction of anthropogenic emissions of greenhouse gas by displacing an equivalent volume of electricity that would otherwise be generated by the most expensive thermal power plants tied into the national grid. This expected outcome can be traced back to the expansion plans, dispatch procedures, and small power purchase policies of the Ceylon Electricity Board. These plans, procedures and policies are discussed in greater detail in Section B of the PDD.

Each year, the CEB prepares an annual energy demand forecast for each of the 8,760 hours in a year. The CEB determines the power supply forecast based on strict merit order beginning with the power plant with the lowest generation cost per kilowatt hour. Small-scale renewables, including the projects in this PDD, are not included in the supply forecast. Instead, the CEB buys small hydropower output and other small-scale renewable energy generation as a substitute for its highest-cost thermal power output. All four projects presented here will be subject to standard terms of the CEB's small power purchase agreement (SPPA). The purchase price is derived from the CEB's estimated short-run avoided cost of electricity generation, which includes the cost of fuel plus operations and maintenance. **Based on this power pricing formula for renewable energies, all small hydropower producers will only displace electricity from thermal power plants.**

Applying the simplified methodologies specified for small-scale projects, these small hydropower projects will result in an annual emissions avoidance of 0.8496 kilograms of CO₂ equivalent per kilowatt



hour generated (kg CO₂e/kWh). This figure is based on the weighted average emissions of grid-connected thermal power stations operating as of August 2003. Other project benefits include reductions in NO_x and SO_x pollution, generation of short- and long-term local employment, and direct financial contributions to community development projects at each site.

The annual average GHG estimations for the project activity is 49,796 tCO₂e.

Baseline scenario

In absence of the project activity, the equivalent amount of electricity would have been generated from fossil-fuel based power plants

Sustainable development from the project activity

Social and Economic Benefits

- During the construction phase of all of the plants (which is typically about one year in duration) the civil engineering firms undertaking the construction of the plants hire a large number of skilled and unskilled workers from the nearby communities, thereby providing additional employment during the period.
- After commissioning the plants typically have a small complement of staff of 10-15 persons including plant operators, labourers, security staff, etc. Over 50% of these persons are typically hired from the nearby communities.
- In most of the plants, additional roads have been/will be built by EPL to access the power houses. These roads are available for use by the local people and in some cases provide motorable access to their homes where there were only footpaths before.
- During the construction phase various additional work beneficial to the local communities is carried out by EPL free of charge. An example would be the expansion of the playing field of the nearby school using bulldozers and excavators in the case of the Hulu Ganga Phase I project.
- After every project is commissioned EPL provides a separate Rs 200,000 (\$2,000) per year budget for the local community to use for community development projects of their choice.
- All power from the power plants are carried to the CEB grid through the existing 33 kV distribution lines in the area. If these lines are not working for any reason EPL cannot sell its power. In rural Sri Lanka where all of the plants built/being built by EPL are located there are frequent breakdowns in supply and the CEB local authorities take their own time to repair these breakdowns. After EPL builds this power plant it will pay a retainer to the local CEB authorities to cover the costs associated with repair of the distribution lines in the area. As a result the grid outage rates suffered by others consumers in the area also reduced significantly.
- The four projects generate electrical energy using water. If they had not been constructed the same amount of energy would have been generated using oil which is imported. The country would therefore save on the foreign exchange required to import the oil.

A.2. Location of project activity

A.2.1. Host Party(ies)

>>

Sri Lanka

The Government of Sri Lanka ratified the UNFCCC on 23 November 1993. The country subsequently acceded to the Kyoto Protocol on September 3, 2002.

**A.2.2. Region/State/Province etc.**

>> For Hapugastenne Phase I and Phase II projects- Sabaragamuwa Province, Ratnapura District
For Hulu Ganga I and Hulu Ganga II projects- Central Province, Kandy District

A.2.3. City/Town/Community etc.

>>
For Hapugastenne Phase I and Phase II projects- Near the town of Ratnapura
For Hulu Ganga I and Hulu Ganga II projects- Near the village of Panwila, north of the town of Kandy

A.2.4. Physical/ Geographical location

>>
Hapugastenne Phase I and Phase II Small Hydropower Projects are both located within close proximity of one another at the Hapugastenne Estate. Both projects are found at the following coordinates:

Longitude N 6° 42.1' / Latitude E 80° 30.3'

The next two projects, although quite close, are two distinct power generation facilities. They are located at the following coordinates:

Hulu Ganga Phase I Small Hydropower Project
Longitude N 7° 23.5' / Latitude E 80° 44.8'

Hulu Ganga Phase II Small Hydropower Project
Longitude N 7°23.3' / Latitude E 80° 44.5'

A.3. Technologies and/or measures

>>
All four of the project sites involve installation of a run-of-river hydropower plant system using well-established technologies. Run-of-river hydropower facilities are emissions-free and considered one of the best forms of low impact renewable energy available today. The civil structures at each project site consist of a gated weir designed to store a low volume of water, an intake arrangement, a channel, a desilting/forebay arrangement, a penstock, a powerhouse and a tailrace. Run-of-river hydropower has very low impact on river flow volumes and all water diverted to the powerhouse is returned to the main stream. The Hapugastenne projects run on a Pelton Turbine whereas the Hulu Ganga projects rely on a Francis type turbine. Both turbine types have well-demonstrated application around the world and are considered optimal for the particular sites being developed. Detailed engineering information on all four projects is available with the project operator, EPL.

All electricity generated from these projects will be sold to the CEB, the monopoly government-owned power utility. The CEB will dispatch the electricity from the hydropower projects to end-users connected to the national power grid.

**A.4. Parties and project participants**

Party involved (host) indicates a host Party	Private and/or public entity(ies) project participants (as applicable)	Indicate if the Party involved wishes to be considered as project participant (Yes/No)
Sri Lanka (Host)	Eco Power (Private) Limited (EPL)	No
Netherlands	International Finance Corporation as Trustee of the IFC-Netherlands Carbon Facility (INCaF) And Netherlands' Ministry of Infrastructure and the Environment (IenM)	Yes

The following are the main Project Participants.

Eco Power (Private) Limited (EPL) is a private Sri Lankan company that will build and operate the four small hydro power plants. EPL's sole business activity is to build and operate small hydro power plants in Sri Lanka. Up to April 2003, the company had commissioned six (6) such plants with a combined total installed capacity of 14.5 MW. EPL is seeking registration of its small hydropower projects under the Clean Development Mechanism as a means to buffer the higher investment and financial risks associated with the renewables energy marketplace in Sri Lanka.

C-Quest Capital (CQC), an energy and environmental management consulting firm, is the exclusive representative of EPL for the purposes of the marketing and sale of emissions reductions from the four projects described in this document. CQC is also the designated official contact for the proposed CDM project activities.

The Netherlands represented by its Ministry of Housing, Spatial Planning and the Environment acting through the International Finance Corporation, in its individual capacity and as a Trustee of the IFC-Netherlands Carbon Facility (INCAF) Facility. IFC-Netherlands Carbon Facility (INCAF) Facility is an arrangement under which the International Finance Corporation (IFC) will purchase greenhouse gas (GHG) emission reductions for the benefit of the Government of the Netherlands using the Clean Development Mechanism. The Netherlands will use these emission reductions to help meet its commitments under the Kyoto Protocol. EPL and INCAF have entered into a preliminary agreement (a letter of intent) by which EPL agrees to sell and INCAF agrees to purchase eligible greenhouse gas emissions reductions associated with the projects described in this PDD.

All the project participants mentioned above are designated official contacts for the proposed CDM project activities.

Sri Lanka is the host country for this project. The Government of Sri Lanka ratified the UNFCCC on 23 November 1993. The country subsequently acceded to the Kyoto Protocol on September 3, 2002. The Government recently established its Designated National Authority, which is now registered with the CDM Executive Board.

**A.5. Public funding of project activity**

>>

Financing for the projects will come from the project sponsor, EPL and from commercial banks in Sri Lanka. No Annex I Party public funding is directly involved in the proposed projects.

A.6. Debundling for project activity

>>

The proposal consists of four stand-alone small-scale hydropower plants. The proposed projects are not debundled components of a larger project. These projects are presented in one PDD based on the fact that (a) the combined size is less than 15MW, and (b) the projects share a common monitoring plan.

SECTION B. Application of selected approved baseline and monitoring methodology**B.1. Reference of methodology**

>>

AMS-I.D: Renewable electricity generation for a grid, Version 05: 25 February 2005

B.2. Project activity eligibility

>>

All four projects involve the sale of electricity from small-scale hydropower plants to the national monopoly grid manager, the Ceylon Electricity Board. This scenario is the only option available to the project developer and it corresponds precisely with the SSC CDM category I.D.

Applicability condition of AMS-I.D version 5	How the project fulfills the eligibility criteria
1. This category comprises renewable energy generation units, such as photovoltaics, hydro, tidal/wave, wind, geothermal, and biomass, that supply electricity to an electricity distribution system that is or would have been supplied by at least one fossil fuel or non-renewable biomass fired generating unit	The project activity is renewable energy generation from hydro power plants. Hence it fulfills this applicability criteria
2. If the unit added has both renewable and non-renewable components (e.g. a wind/diesel unit), the eligibility limit of 15MW for a small-scale CDM project activity applies only to the renewable component. If the unit added co-fires [non-renewable biomass and fossil fuel, the capacity of the entire unit shall not exceed the limit of 15MW.	The project activity has only renewable component of total 13.568 MW capacity which is within the capacity limit of 15 MW. Thus the project fulfills this applicability criteria
3. Biomass combined heat and power (co-generation) systems that supply electricity to a grid are included in this category. To qualify under this category, the sum of all forms of energy output shall not exceed 45 MW _{thermal} . E.g., for a biomass based co-generating system the rating for all the boilers combined shall not exceed 45 MW _{thermal}	The project does not involve any co-generation system. Hence this criteria is not applicable to the project activity.



B.3. Project boundary

>> The boundaries for the four projects encompass the physical, geographical site of the four hydropower plants.

B.4. Establishment and description of baseline scenario

>>

The CEB, as a monopoly entity that controls the country's power grid, prepares annual demand and supply forecasts, manages most power generation facilities in Sri Lanka (except for thermal power plants introduced in the past eight years), sets the terms of small power purchase agreements and leads development of grid expansion plans.

The expansion plan (updated every two years) is designed to respond to two key concerns. First, electricity demand in Sri Lanka is growing at an average annual rate of 7-8%, which will require major investments in new generation facilities over the next decade. Second, further exploitation of large scale hydro resources (which have historically provided a large percentage of total power) is becoming increasingly difficult owing to social and/or environmental impacts associated with such developments. The CEB's 2002-2016 national expansion plan, therefore turns to thermal power plants as the primary solution to meeting the country's growing energy needs. Specifically, CEB forecasts thermal power generation capacity to increase from its 2002 level of 751 MW to a target level of 2,754 MW in 2016. This forecast reflects a steady trend of increasing reliance on thermal power sources since the late 1990s. For example, between 1997 and 2003, the country added 724 MW of thermal power generation capacity. On the other hand, facilities less than 15 MW in size, which includes the small hydropower plants described in this PDD, are not incorporated into the national expansion plan. So, all small hydropower and other renewables are not part of the default power generation baseline.

Baseline uncertainties and alternative scenarios Based on the facts regarding how CEB prepares and guides both the dispatch of current energy supply as well as the options for future energy investments, the most likely baseline scenario in Sri Lanka is the one that conforms to the CEB's current generation mix plus the base case expansion plan. The major uncertainties related to this scenario are (i) emergency conditions that lead to generation short-falls and power outages; and (ii) delays in building new power generation facilities. Either of these scenarios is likely to increase average emissions levels because (a) older, higher emissions thermal power plants will have to be used longer and for more operating hours per year, and (b) emergency diesel generators will be required to overcome generation shortfalls. A third possible scenario is a substantial increase in small-scale renewable energy or a greater investment in large-scale hydropower. However, as the earlier discussion emphasized, small-scale hydropower and wind power have very limited potential (100-200 MW for small-scale hydropower) compared to the total expected growth in generation over the next 15 years. Similarly, the country has nearly exhausted its options for large-scale hydropower because of environmental and social concerns.

The latest version of the small-scale CDM project guidelines issued on January 24, 2003, offers two options for calculating baseline emissions of category I.D. projects. The baseline for the Hapugastenne and Hulu Ganga projects is based on the second option identified in Appendix B of the simplified modalities and procedures for small-scale CDM. According to this option the baseline is defined as the kWh produced by the small hydropower plants multiplied by an emission coefficient (measured in KgCO₂/kWh) calculated in a transparent and conservative manner as follows:

The average of the "approximate operating margin" and the "build margin: where:

- (i) The “approximate operating margin” is the weighted average emissions (in kg CO₂equ/kWh) of all generating sources serving the system, excluding hydro, geothermal, wind, low-cost biomass, nuclear and solar generation;
- (ii) The “build margin” is the weighted average emissions (in kg CO₂equ/kWh) of recent capacity additions to the system, which capacity additions are defined as the greater (in MWh) of most recent 20% of existing plants or the 5 most recent plants.

The operating margin and build margin are derived from information available in the CEB 2002-2016 expansion plan. The plants that are included in the operating margin are those known to be on-line as of August 2003, when this PDD was first prepared. The calculations that quantify the baseline and expected emissions offsets are shown in Section E. In looking at the expansion plan, the CEB’s intent is clearly to build up coal power. However, experience over the past five years shows that the CEB expansion plan rarely adheres to schedule – delays in commissioning new plants can continue for many years. Thus, to be conservative, the PDD calculates the baseline emissions based uniquely on the power plants already operational as of August 2003.

Table 2: Ceylon Electricity Board base case supply forecast

Existing and Committed Hydro Power Plants				
Plant Name	Capacity (MW)	Annual (GWh)	Average	Energy
EXISTING				
Laxapana Complex	335	1432		
Mahaweli Complex	660	2100		
Samanalawewa	120	361		
Inginiyagala	11	---		
UdaWalawe	6	---		
Nilambe	3	---		
Private hydro power	12.25	---		
COMMITTED				
Kukule (End 2003)	70	303		
Upper Kotmale (2008)	150	530		
TOTAL HYDRO POWER	1367.3	4726		
Existing, Committed and Additional Thermal Power Plants				
EXISTING				
Kelanitissa station				
Old gas turbines	96	600		
New gas turbines	115	813		
Steam (fuel oil)	40	250		
Combined cycle plant (early 2003)	165	1253		
Sapugaskanda Station				
Diesel	72	488		
Diesel extension	72	444		
Independent Power Producers				
Lakdhanavi	22.5	156		
Asia Power Ltd	51	330		
Colombo Power (Pvt) Ltd	64	420		
Diesel Plant Matara (2002)	24.8	136		
COMMITTED				



Pielstick (Jan 2003)	22	149
Independent Power Producers*		
Kelanitissa AES CCY (2003)	163	1314
Diesel Plant Horana (2003)	24.8	136
TOTAL THERMAL POWER	932.1	6489.0
EXPANSION PLAN ADDITIONS (in sequence)		
Kerawalapitiya combined cycle (2006)	300	
Gas turbine (2007)	105	
Coal Steam West Coast I (2008)	300	
Coal Steam West Coast II (2010)	300	
Coal Steam West Coast III (2012)	300	
Coal Steam Trincomalee I (2013)	300	
Coal Steam Trincomalee II (2015)	300	
Gas Turbines (2016)	175	

* IPP facilities were commissioned as build, operate and own contracts with CEB.

The table above presents the CEB's supply response to the base demand forecast. The CEB's sensitivity analysis of key parameters (overall demand, impact of demand side management measures, changes in discount rate, and a change in oil price) shows that the timing of power plant additions may shift slightly (1-3 years) but the overall trend is still one of aggressive capacity expansion.

As per the instructions for small-scale projects, the power plants considered for the baseline include only those grid-connected power facilities in operation as of the date of preparation of the PDD (August 2003). Table 3 lists the thirteen (13) power plants included for purposes of estimating the approximate operating margin of the baseline. It is important to note that both of the combined cycle plants listed in the table (JBIC and AES) are only operating the open cycle at this time and that emissions factors at the two plants are therefore higher than they would be with both cycles in operation.

Table 3: Power plants included in the Sri Lanka approximate operating margin

	CEB-operated facilities	Capacity (MW)	Date(s) commissioned
1	Kelanitissa gas turbines (old)	96	1980-82
2	Kelanitissa gas turbines (new)	115	1997
3	Kelanitissa steam power units	40	1962-63
4	Sapugaskanda diesel plant	72	1984
5	Sapugaskanda diesel extension	72	1997-99
6	Pielstick diesel plant	22	2003
7	Combined cycle plant 1 (JBIC-financed)	165	2002-2003
	Independent Power Producers (BOOT contracts)		
8	Lakdhanavi diesel engine	22.5	1997
9	Asia Power Ltd diesel engine	51	1998
10	Colombo Power Ltd diesel engines	64	2000
11	Matara diesel plant	24.8	2002
12	Combined cycle plant 1 (JBIC-financed)	165	



	CEB-operated facilities	Capacity (MW)	Date(s) commissioned
13	Horana diesel plant	24.8	2003
14	Combined cycle plant 2 (AES with an ADB loan guarantee)	163	2003

The baseline build margin is based on the list of *all* grid-connected power plants currently in operation. Table 4 summarizes that list, presented in order of the year the facility entered into operation.

Table 4: Power plants considered for preparation of the build margin

	Facility	Fuel	Commission date	Capacity (MW)
1	Old Laxapana	Hydropower	1950 & 58	50
2	Kelanitissa steam power units	Fuel oil	1962-63	40
3	Inginiyagala	Hydropower	1963	11
4	Wimalasurandra	Hydropower	1965	50
5	Polpitiya	Hydropower	1969	75
6	UdaWalawe	Hydropower	1969	6
7	New Laxapana	Hydropower	1974	100
8	Ukuwela	Hydropower	1976	38
9	Kelanitissa old gas turbines	Auto diesel	1980 & 82	96
10	Bowatenna	Hydropower	1981	40
11	Canyon hydro	Hydropower	1983 & 88	60
12	Sapugaskanda old diesel	Residual fuel oil	1984	72
13	Victoria	Hydropower	1985	210
14	Kotmale	Hydropower	1985	201
15	Randenigala	Hydropower	1986	122
16	Nilambe	Hydropower	1988	3
17	Rantambe	Hydropower	1990	49
18	Samanalawewa	Hydropower	1992	120
19	Kelanitissa new gas turbines	Auto diesel	1997	115
20	Sapugaskanda new diesel ext. (4 units)	Residual fuel oil	1997	36
21	Lakdhanavi diesel engine	Auto diesel	1997	22.5
22	Asia Power Ltd diesel engine	Auto diesel	1998	51
23	Sapugaskanda new diesel ext. (4 units)	Residual fuel oil	1999	36
24	Colombo Power Ltd diesel engines	Auto diesel	2000	64
25	Matara diesel plant	Auto diesel	2002	24.8
26	Pielstick diesel plant	Fuel oil	2003	22
27	Combined cycle plant 1 (JBIC-financed)	Fuel oil	2002	165
28	Horana diesel plant	Auto diesel	2003	24.8
29	Combined cycle plant 2 (ADB guarantee)	Fuel oil	2002	163



The build margin is defined as the greater of the most recent 20% or the 5 most recent plants. In this case, the most recent 20% is applicable, and hence the build margin is therefore the last six plants added to the grid: Colombo, Matara, Pielstick, Horana, and two combined cycle power plants (shown in grey in Table 4).

B.5. Demonstration of additionality

>>

Power generation capacity expansion is an urgent issue in Sri Lanka. Energy demand in the country has been growing at an average rate of about 7-8% per annum in the past 20 years, a trend that is expected to accelerate over the next decade. According to the CEB, further exploitation of large hydro resources is becoming increasingly difficult owing to social and/or environmental impacts associated with large-scale developments. In addition, the extensive reliance on hydropower makes the power system of this island nation overly vulnerable to drought. Severe drought led to power cuts in 2001 and the CEB has expressed its concern that cuts could occur again in the absence of capacity expansion.

The CEB is the government-owned monopoly power utility that prepares and manages the implementation of the country's power generation expansion plan. To meet the rapid growth in energy demand, the CEB expansion plan forecasts the addition of 2,690 MW in installed capacity between 2002 and 2016. The generation expansion plan takes into consideration contributions from existing and committed power facilities, and identifies additional capacity needs to meet future energy demand at the least possible generation cost. While the existing generating system is predominantly based on hydropower (60% of installed capacity), the base case expansion plan focuses on growth in thermal power. Specifically, it includes only 220 MW of hydro power additions (in 2004 and 2008) and 2,470 MW of thermal power additions. Annex 3 summarizes the data, methods and results of the CEB expansion plan.

The potential for small scale hydropower to access the marketplace in Sri Lanka is restricted by the fact that CEB controls access to and the terms for power production. The CEB is the major owner and operator of most power plants in Sri Lanka and is responsible for issuance of power production licenses. All power generation licenses specify that output must be sold to the CEB. Over the past five-seven years, the CEB has increasingly turned towards commissioning power plants on build, operate, own and transfer (BOOT) contracts with private operators. Note that all BOOT contracts have been for the construction of thermal power plant facilities. The CEB nevertheless maintains control of the process of identifying and licensing these new facilities. Similarly, all small-scale projects must have the preapproval of the CEB and developers must accept the CEB's energy purchase price that changes annually-not based on verifiable, objective criteria, but rather changes in accordance with the CEB internal calculations.

This discussion serves to highlight the dominating role of the CEB in setting the specific market and policy conditions for sector expansion. Given the tremendous growth in electricity demand, the CEB has instituted a number of policies and practices that strongly favor investments in thermal generation combined with only two new investments in large-scale, publicly-managed hydropower facilities. As the rest of this section demonstrates, the four small-scale hydropower projects in this PDD are considered additional to the Sri Lanka energy sector emissions baseline based on an analysis of selected barriers listed in Attachment A to Appendix B, the simplified project design document for small-scale CDM project activities (SSC-PDD). Specifically, we demonstrate that the projects face significant barriers related to (i) heightened investment risk (common to all small-scale renewable investments in Sri Lanka), (ii) low market penetration of run-of-river small hydropower technology, and (iii) non-transparent procedures in the calculation of tariff schedules for small hydropower operators.

(i) Investment risk barrier



Energy generation investment opportunity in Sri Lanka is relatively limited. In that limited market, small hydropower investments are subject to much higher risks than investments in thermal power projects. The difference in level of risk is in large part linked to the power purchase terms set by the CEB. In the case of thermal power plants the CEB pays a capacity charge sufficient to cover all up-front capital costs including an agreed rate of return on the investment. In addition, separate payments are made for energy on a pass through basis. Thus, private thermal power plant operators and investors are guaranteed a no risk rate of return on their investment provided the technical aspects of the plant are sound.

In contrast, investors and operators of small hydropower facilities (and other small renewables) do not receive a capacity charge. Instead, small hydropower developers are paid based strictly on the CEB's short-run avoided costs. These avoided costs can fluctuate considerably from year to year and small hydro developers can and have in the past suffered losses in individual years. Unlike thermal power plant operators, small hydropower investors cannot claim a payment to compensate for drought-induced generation shortfalls. These arrangements act as a disincentive to investments in small-scale hydropower and argue for the additionality of the EPL investments at Hapugastenne and Hulu Ganga.

(ii) Low market penetration/uncommon practice barrier

Previous studies conclude that the country has limited potential for small-scale hydropower (100-200MW). A World Bank project document notes that installed small hydropower was 30 MW at the end of 2001, which is equal to less than 2% of total capacity in the country. Looking at the impact of the four projects in this PDD, it is clear that they make very marginal contributions to the current and future generation mix. For example, the four projects in this PDD will generate a combined 56.6 GWh/year, which corresponds to only 0.82% of the national annual electricity generation of 6,843 GWh in 2000, and a mere 0.39% of the total capacity of 14,278 GWh forecast in 2012. With an aggressive schedule for future expansion of thermal power capacity, small scale hydropower will continue to be a marginal technology in Sri Lanka with low market penetration, unless CDM revenues enable small hydro developers to take on the higher risks associated with investing in small run of river hydro plants.

(iii) Barriers related to uncertainties in power purchase agreement conditions

Small-scale hydropower investors like EPL also face uncertainties and risks related to power purchase terms of the CEB, a monopoly utility. Each year the CEB sets a power purchase agreement price level for the wet and dry seasons. That figure is based on a 3-year running average of avoided costs. However, the CEB does not transparently demonstrate to small power producers the methodology for calculating these rolling averages. As a result, private investors have considerable difficulty predicting the direction of price changes and the degree of fluctuation from one year to the next. For example, the CEB recently announced the 2004 prices for small hydro independent power producers. Despite one of the worst droughts in decades and a steep rise in oil prices, the CEB reduced the tariff 28% below its 2003 level. The only recourse is for producers to enter into arbitration over rate calculations. However, EPL has learned from experience that arbitration can easily continue, with no resolution, for several years.

This analysis of three different barriers suggests that small hydropower investments like the ones at Hapugastenne and Hulu Ganga are additional to a national baseline which is clearly oriented to favor large-scale thermal investments combined with a limited number of large-scale, publicly managed hydropower investments.

Faced with the multiple investment barriers described here, EPL began in early 2000 to evaluate the possibility of improving project rates of return and reducing its financial risks through registration of its projects under the CDM.

B.6. Emission reductions

B.6.1. Explanation of methodological choices

>> Calculation of the EPL project GHG emissions reductions apply a weighted average emissions factor for all thermal plants that are operational on the national grid as of August 2003. Appendix B of the simplified M&P for CDM small-scale project activities does not provide specific formulae for this calculation.

Project Emissions

There are limited estimated anthropogenic emissions of greenhouse gases due to the project activities. These Emissions stem from investment activities to construct the hydropower facilities including emissions from vehicles transporting equipment and personnel as well as emissions from use of heavy machinery and a generator at the construction site. The project construction emissions are calculated using the following formulae:

For transportation-related emissions:

Fuel for transportation	x	2.68
(litres of fuel)		(kg CO ₂ /litre)

For small engine-related emissions (cement mixer and generator):

Fuel for operation	x	2.68
(litres)		(kg CO ₂ /litre)

Hence, the total project emissions due to transportation and small engine-related is:

Total consumption of fuel	x	2.68
(litres of diesel)		(kg CO ₂ /litre)

Project Emissions: 298,690 kgCO₂ or 298.7 tons CO₂ equivalent

These emissions occur only during the site preparation and construction stage and are to be deducted from year 1 emission offset totals.

Leakage Emissions

At the Hapugastenne Phase I site, the local tea plantation had been operating a very small hydropower station with approximately 40 kW capacity. This facility was shut down due to its advanced age at around the time Hapugastenne Phase I project was commissioned. Although the timing coincides, the decision on shutting down the aged mini-hydro facility is not directly tied to the new power supply (the EPL facility will sell directly to the grid whereas the existing facility was only used for on-site needs at the tea plantation). This clarification notwithstanding, no leakage issues arise as a result of the proposed project activities.

Baseline Emissions

The baseline for the proposed projects is the weighted average emissions of the current generation mix of thermal plants expressed in KgCO₂/year. To ensure clarity and replicability of the results, the baseline GHG calculations are broken down into five steps. All variables are assigned a letter code (A, B, C, D....) which allows for easy cross-reference to the summary table that demonstrates the values obtained using these formulae.



Step 1: Calculate the relative power contribution of each thermal power plant on the grid (expressed as a percentage of total kWh generated).

This calculation is based on the following series of equations.

a. Determine expected total operating hours/year:

The following equation assumes all power plants are operating at optimal load levels. This allows for the most conservative estimate of emissions given that emissions factor tend to rise when thermal power plants operate at low load levels.

$$\begin{array}{lcl} \text{Total operating} & & 8760 \text{ hours/year} - \text{maintenance days} - \text{forced outage rate} \\ \text{hours/year} & = & (\%) \end{array}$$

$$[D] \quad [(A - (B * 24 \text{ hours})) - ((100 - C) / 100)]$$

Data source: CEB

b. Determine maximum annual energy output (kWh/year) of each power plant

$$\begin{array}{lcl} \text{Annual energy} & & \text{Operating hours} * \text{MW} * 10^9 \\ \text{output (kWh/yr)} & = & \end{array}$$

$$[F] \quad [D * E * 10^9]$$

Data source: CEB

c. Calculate percentage power contribution of each power plant (% of kWh/year)

$$\begin{array}{lcl} \text{Percentage power} & & \text{Annual output of each plant} / \\ \text{of each plant (\%)} & = & \text{Sum of output of all plants} \end{array}$$

$$[G] \quad [F / \sum F_1 \dots n]$$

Step 2: Calculate the emissions factor for each thermal power plant.

a. Determine each plant's heat rate (MJ/MWh)

$$\begin{array}{lcl} \text{Plant heat rate} & & (1 / \text{plant conversion efficiency}) * 3.6 * 10^3 \\ \text{(MJ/MWh)} & = & \end{array}$$

$$[J] \quad [(1 / I) * 3.6 * 10^3]$$

Data source: CEB for plant conversion efficiency rates; IPCC for terajoule conversion factor of $3.6 * 10^3$ joules/MWh.

b. Estimate an adjusted carbon content of fuel for each power plant

$$\begin{array}{lcl} \text{Adjusted carbon} & & \text{carbon content of each fuel} * \text{combustion} \\ \text{content of each fuel} & = & \text{efficiency of power plant} \\ \text{(TC/TJ)} & & \end{array}$$

$$[M] \quad [K * L]$$

**c. Calculate emissions factor (kgC/MWh) of each power plant**

$$\begin{aligned} \text{Emissions factor (kgC/MWh)} &= (\text{Heat rate * adjusted carbon content of fuel * } 10^3) / 10^6 \\ [N] &[J * M * 10^3 / 10^6] \end{aligned}$$

d. Convert kgC/MWh calculation to CO₂ emissions per kilowatt hour

$$\begin{aligned} \text{CO}_2 \text{ emissions (kg CO}_2\text{/kWh)} &= (\text{KgC/MWh * } 44/12) / 10^3 \\ [O] &[(N * 44/12) / 10^3] \end{aligned}$$

Step 3: Calculate the emissions coefficient for the “approximate operating margin” defined in accordance with CDM Executive Board guidance as the weighted average emissions of all sources serving the system, excluding hydro, geothermal, wind, low-cost biomass, nuclear and solar generation.

a. Determine weighted average emissions of each power plant

$$\begin{aligned} \text{Weighted average emissions (kg CO}_2\text{/kWh)} &= \text{CO}_2 \text{ emissions of each plant / percent contribution of power to the grid} \\ [P] &[O / G] \end{aligned}$$

b. Sum weighted average emissions

$$\begin{aligned} \text{Weighted average emissions of all plants (kg CO}_2\text{/kWh)} &= \text{Sum of emissions factor for power plants 1 through n} \\ &[\Sigma P_1 \dots n] \\ [Q] \end{aligned}$$

This calculation results in a figure of 0.8719 kgCO₂/kWh as the approximate operating margin of all non renewable energy on the grid at the current time.

Step 4: Calculate the emissions coefficient for the “build margin” defined as the weighted average emissions of recent capacity additions to the system, defined as the lower of the most recent 20% of plants built or the 5 most recent plants;

The build margin includes the five most recent power plants commissioned. These were identified in Section B.4 of the PDD. The result can be summarized in the following formula:

$$\begin{aligned} \text{Weighted average emissions of the five most recent power} &= \text{Sum of the weighted emissions factors for the five most recent power plants} \end{aligned}$$

plant additions to the
grid
(kg CO₂/kWh)

[R]

[Σ five most recent power plants]

The above calculation results in a figure of 0.8273 kgCO₂/kWh as the weighted average build margin at this point in time.

Step 5: Calculate the average of the operating margin and the build margin:

$$[Q + R] = (0.8719 + 0.8273) / 2 = 0.8496 \text{ kgCO}_2/\text{kWh}$$

This figure represents the estimated annual emissions offset value that would result from the implementation of the four EPL small hydropower projects.

B.6.2. Data and parameters fixed ex ante

(Copy this table for each piece of data and parameter.)

Data / Parameter	EF _y
Unit	kgCO ₂ /kWh
Description	Emission Coefficient
Source of data	Ceylon Electricity Board (CEB) Expansion Plan 2002-2016
Value(s) applied	0.8496
Choice of data or Measurement methods and procedures	The operating margin and build margin are derived from information available in the CEB 2002-2016 expansion plan. The plants that are included in the operating margin are those known to be on-line as of August 2003, when this PDD was first prepared. The calculations that quantify the baseline and expected emissions offsets are shown in Section E. In looking at the expansion plan, the CEB's intent is clearly to build up coal power. However, experience over the past five years shows that the CEB expansion plan rarely adheres to schedule – delays in commissioning new plants can continue for many years. Thus, to be conservative, the PDD calculates the baseline emissions based uniquely on the power plants already operational as of August 2003.
Purpose of data	Calculation of baseline emissions
Additional comment	

B.6.3. Ex-ante calculation of emission reductions

>>

Project Emissions

There are limited estimated anthropogenic emissions of greenhouse gases due to the project activities. These Emissions stem from investment activities to construct the hydropower facilities including emissions from vehicles transporting equipment and personnel as well as emissions from use of heavy machinery and a generator at the construction site.



Deduction of construction-related emissions. Section B.6.1 provides formulae for calculating the project-related emissions. The following table illustrates the actual emissions resulting from each of the four projects in this PDD. These emissions occur only once during the construction phase of the project. The total project-related emissions the sum of all four project sites is 298,690 kgCO₂e or 298.7 tCO₂e.

Emissions During Construction- Hapugastenne Phase I and Phase II Plants (Same civil works for both plants)¹

Construction Item	Units	Quantity	No of Truck Loads	Round trip distance to site (km)	Diesel Fuel Consumption of Truck (km/liter) or Liters/Hour for Cement Mixer/Generator	Total Diesel Fuel Consumption (liters)
Aggregate	Cu. Met.	3,500	350	200	5	14,000
Sand	Cu. Met.	1,750	175	175	6	5,104
Cement	50 kg Bags	28,000	140	250	6	5,833
Steel	Tons	190	38	240	6	1,520
Penstock pipes	No.	680	170	250	5	8,500
Cement mixer	Hours	1,400			5	7,000
Generator (250 kVa)	Hours	1,200			15	18,000
Total						5,9958

Total Diesel Fuel Consumed

59,958	x	2.68 kg CO ₂ /litre	=	160,686 kg CO ₂	=	160.7 tons CO₂e
--------	---	--------------------------------	---	----------------------------	---	-----------------------------------

Construction Emissions from Hulu Ganga Phase I Hydropower Plant²

Construction Item	Units	Quantity	No of Truck Loads	Round trip distance to site (km)	Diesel Fuel Consumption of Truck (km/liter) or Liters/Hour for Cement Mixer/Generator	Total Diesel Fuel Consumption (liters)
Aggregate transport	Cu. Met.	1,850	185	140	5	5,180
Sand transport	Cu. Met.				6	

¹ Hapugastenne I and II plants were commissioned before the registration of the project activity. The total diesel consumption for these two plants has been verified by DOE during the validation time.

² Hulu Ganga I plant was commissioned before the registration of the project activity. The total diesel consumption has been verified by DOE during the validation time.



		925	93	150		2,325
Cement transport	50 kg Bags	14,800	74	100	6	1,233
Steel transport	Tons	140	29	300	6	1,450
Penstock pipe transport	No.	130	65	300	5	3,900
Cement mixer	Hours	740			5	3,700
Generator (250 kVa)	Hours	500			15	7,500
Total						25,288

Total Diesel Fuel Consumed

$$25,288 \times \frac{2.68 \text{ kg CO}_2/\text{litre}}{1} = 67,733 \text{ kg CO}_2 = 67.8 \text{ tons CO}_2\text{e}$$

Emissions During Construction –Hulu Ganga Phase II Plant³

Construction Item	Units	Quantity	No of Truck Loads	Round trip distance to site (km)	Diesel Fuel Consumption of Truck (km/liter) or Liters/Hour for Cement Mixer/Generator	Total Diesel Fuel Consumption (liters)
Aggregate transport	Cu. Met.	1,800	180	150	5	5,400
Sand transport	Cu. Met.	900	90	160	6	2,400
Cement transport	50 kg Bags	14,400	72	110	6	1,320
Steel transport	Tons	130	26	310	6	1,343
Penstock pipe transport	No.	140	70	310	5	4,340
Cement mixer	Hours	720			5	3,600
Generator (250 kVa)	Hours	520			15	7,800
Total						26,203

Total Diesel Fuel Consumed

$$26,203 \times \frac{2.68 \text{ kg CO}_2/\text{litre}}{1} = 70,225 \text{ kg CO}_2 = 70.2 \text{ tons CO}_2\text{e}$$

³ The total diesel consumption for Hulu Ganga II plant is the actual value provided by Squire Mech Engineering (Pvt) Ltd via letter dated 23rd July 2013.

kg CO₂tons CO₂e**Leakage Emissions**

No leakage emissions are expected from the project activity.

Baseline Emissions

Each of the four small hydropower facilities is expected to operate for 30 years. Three of the facilities began operating in 2001, 2002, and 2003, respectively. The fourth facility, Hulu Ganga II, is expected to be operational in 2006. Using a weighted average emission factor of 0.8496 tons CO₂/MWh for the thermal power plants in operation as of August 2003, the expected annual emissions reductions for any twelve-month period for all four hydropower plants combined is estimated at 49,796 tons of CO₂.

Electricity Generation and Emissions Reduction Summary

Proposed hydropower plant	Capacity rating (MW)	Capacity factor (%)	Average annual electricity generated (10⁶ kWh)	Emissions factor (kg CO₂/kWh)	Annual emissions reductions (tCO₂)
Hapugastenne I	5.052	40	17.702208	0.8496	15,040
Hapugastenne II	2.526	86	19.029874	0.8496	16,168
Hulu Ganga I	3.000	39.4	10.354320	0.8496	8,797
Hulu Ganga II	2.990	44	11.524656	0.8496	9,791
Total	13.568		58.611058		49,796

B.6.4. Summary of ex-ante estimates of emission reductions

Year	Baseline emissions (tCO ₂ e)	Project emissions (tCO ₂ e)	Leakage (tCO ₂ e)	Emission reductions (tCO ₂ e)
Year 1	49,796	0	0	49,796
Year 2	49,796	0	0	49,796
Year 3	49,796	0	0	49,796
Year 4	49,796	0	0	49,796
Year 5	49,796	0	0	49,796
Year 6	49,796	0	0	49,796
Year 7	49,796	0	0	49,796
Year 8	49,796	0	0	49,796
Year 9	49,796	0	0	49,796
Year 10	49,796	0	0	49,796
Total	497,960	0	0	497,960
Total number of crediting years	10			
Annual average over the crediting period	49,796	0	0	49,796

B.7. Monitoring plan

B.7.1. Data and parameters to be monitored

(Copy this table for each data and parameter.)

Data / Parameter	H1-mmyy-kWh
Unit	kWh
Description	Hapugastenne Phase I project net electricity output
Source of data	Monthly statements on net electricity supplied to the grid
Value(s) applied	17,702,208
Measurement methods and procedures	The data will be measured continuously and recorded on a monthly basis from the monthly statements.
Monitoring frequency	The meter used will be electronic bi-directional meter and will be calibrated annually. The data will be cross-checked with the invoices raised by the PP on CEB (Ceylon Electricity Board).
QA/QC procedures	The data will be archived electronically and manually on paper. Data will be kept for two years after the end of crediting period or date of the last issuance of CERs for each project, whichever is later.
Purpose of data	To calculate baseline emissions
Additional comment	



Data / Parameter	H2-mmyy-kWh
Unit	kWh
Description	Hapugastenne Phase II project net electricity output
Source of data	Monthly statements on net electricity supplied to the grid
Value(s) applied	19,029,874
Measurement methods and procedures	The data will be measured continuously and recorded on a monthly basis from the monthly statements.
Monitoring frequency	The meter used will be electronic bi-directional meter and will be calibrated annually. The data will be cross-checked with the invoices raised by the PP on CEB (Ceylon Electricity Board).
QA/QC procedures	The data will be archived electronically and manually on paper. Data will be kept for two years after the end of crediting period or date of the last issuance of CERs for each project, whichever is later.
Purpose of data	To calculate emissions
Additional comment	

Data / Parameter	HG1-mmyy-kWh and HG2-mmyy-kWh
Unit	kWh
Description	Hulu Ganga Phase I and Hulu Ganga Phase II project net electricity output
Source of data	Monthly statements on net electricity supplied to the grid
Value(s) applied	10,354,320 for HG 1 11,524,656 for HG 2 Total: 21,878,976
Measurement methods and procedures	The data will be measured continuously and recorded on a monthly basis from the monthly statements.
Monitoring frequency	The meter used will be electronic bi-directional meter and will be calibrated annually. The data will be cross-checked with the invoices raised by the PP on CEB (Ceylon Electricity Board).
QA/QC procedures	The data will be archived electronically and manually on paper. Data will be kept for two years after the end of crediting period or date of the last issuance of CERs for each project, whichever is later. The net generation from Hulu Ganga Phase I and Hulu Ganga Phase II will be monitored by single bi-directional meter.
Purpose of data	To calculate baseline emissions
Additional comment	

B.7.2. Sampling plan

>>

There is no sampling plan required for the project activity

B.7.3. Other elements of monitoring plan

>>



The approved monitoring methodology for renewable electricity generation for a grid is described as follows in appendix B of the simplified M&P for CDM small-scale project activities:

“Monitoring shall consist of metering the electricity generated by the renewable technology.”

This precise methodology will be applied to all four of the EPL small hydropower projects in this PDD.

The choice of methodology reflects the exact recommendations of appendix B for projects that generate renewable energy to a grid. The four small hydropower projects will generate energy that will service the national grid in Sri Lanka.

Two types of data are proposed for the small hydropower project monitoring plan. The first data type is the metered output of electricity from each of the four power plants. The second data type tracks the two major social benefits from the project: short-and long-term employment and EPL’s annual financing of \$2,000 for local development projects as shown in Appendix 5 of the PDD. Each of the four projects will have its own monitoring plan. The ID number identifies the project site, the month and year, and the data type. Electricity output (kWh) and social benefits data (in the form of employment and annual \$2,000 contribution to local development projects) are site-specific. Baseline emissions (KgCO₂/kWh) of grid-connected thermal powerplants are common to all four projects. Electricity output will be metered and recorded monthly. Social benefits will be assessed annually.

Monitoring procedures and responsibilities

The EPL projects are remarkably simple to monitor. The key point is that the only quantitative figure that requires monitoring is the actual generation of electricity from each project site. The steps to ensure this is done correctly are as follows.

First, upon completion of construction, the CEB, as the purchaser of EPL’s power, requires an independent testing of the Facility and an inspection of its equipment. The CEB witnesses the testing procedure. Second, the CEB installs and maintains a primary meter for purposes of billing and payment to EPL. The specification of the meters will be as per the PPA. The Metering Equipment is located in close proximity to the Facility and is sealed. Third, the equipment is tested and calibrated annually. Both parties also have the right to request a calibration at any time if they believe that the meter is dysfunctional.

For monitoring purposes, the project will conform the standard schedule negotiated with the CEB. This involves a CEB reading of the meter at the end of each month for determination of the electrical energy delivered to and accepted by CEB under the terms of the SPPA. EPL power plant operators back this information up by taking daily (sometimes hourly) readings of generation levels and recording them on site. Monitoring data adjustments and uncertainties can only arise if the CEB does not read the meter precisely on the same date each month. In the case of payment of energy supplied, this is handled by the CEB by pro-rating the reading for the number of days in the relevant month. The same approach can be used for emissions reductions.

There is no need for special monitoring training of EPL personnel. The power plants are all automatic and the operators take down periodic readings. If there is some problem with operation, the operator contacts a senior engineer over the phone. In addition, emergencies cannot cause unintended emissions since there is no fuel used by the plants. In the event of a shut-down of the grid, the hydropower facility will automatically switch off and water will no longer be diverted to the turbine.

At the point of project verification, records of electricity generation, meter calibration and CEB power purchase receipts will be available at EPL’s offices in Colombo. The verifier will also be invited to visit individual project sites to confirm the status of operations. The EPL CEO will have direct responsibility



for ensuring adherence to and review of compliance with these procedures. CQC will be responsible for assisting EPL in finalizing the data reporting and recording process and in responding to any issues or corrective actions identified by the project verifier.

Quality Assurance and Quality Control

QA&QC procedures for recording, maintaining and archiving data shall be implemented as part of this CDM project activity. The project proponent will implement QA&QC measures to calibrate and ensure the accuracy of metering and safety aspects of the project operation. The metering devices will be calibrated and inspected properly and periodically, at least once per annum and requirements to ensure accuracy in the readings.

SECTION C. Duration and crediting period

C.1. Duration of project activity

C.1.1. Start date of project activity

>>

The starting date for each of the four small hydro projects is given as the expected commission date as defined as the point when each power plant enters into service. The following table indicates both the date of launch of construction and of commissioning of each plant. Note: Although construction of the Hapugastenne Phase I project started in February 2000, financial closure on the project was only completed in August 2000.

Project	Actual or Anticipated construction start date	Actual commissioning date
Hapugastenne Phase I	02/2000	14/08/2001
Hapugastenne Phase II	01/2002	9/09/2002
Hulu Ganga Phase I	04/2002	3/06/2003
Hulu Ganga Phase II	03/2004	25/10/2006

C.1.2. Expected operational lifetime of project activity

>>

Hapugastenne Phase I	30 years, 0 months
Hapugastenne Phase II	30 years, 0 months
Hulu Ganga Phase I	30 years, 0 months
Hulu Ganga Phase II	30 years, 0 months

C.2. Crediting period of project activity

C.2.1. Type of crediting period

>> Fixed crediting period

C.2.2. Start date of crediting period

>> 01/01/2003 for all the project sites.

C.2.3. Length of crediting period

>>

10 years, 0 months



SECTION D. Environmental impacts

D.1. Analysis of environmental impacts

>>

Environmental impacts

Every small hydro power plant requires approval from the Central Environmental Authority (CEA) which looks at both environmental and social aspects. Because of the small size of the investment, developers prepare an Environmental Report rather than a full blown Environmental Impact Assessment. This Environmental Report corresponds to a format provided by the CEA and the CEA visits the site with a team of experts and grants approval for the project if they are satisfied, after obtaining all necessary clarifications. The Environmental Report includes the following sections:

- Project description (area, weirs/intakes, desilting tanks, head race channels/spills, forebays/desilting tanks, penstocks, power house/tailraces, access roads, and transmission line).
- List of clearances and authorizations obtained, including:
 - Approval of CEB for sale of electricity.
 - Approval from Divisional Secretary for diversion of water.
 - Approval for construction activities.
 - Approval from the Mahaweli Authority if water streams are controlled by them.
- Description of site topography, geology, hydrology, fauna and flora, upstream and downstream users, and social/cultural sensitive areas.
- Discussion of possible impacts such as erosion, land scarring, migration, construction hazards, changes in land use patterns, relocation, etc.
- Description of monitoring program and any mitigatory measures of the project.

A general comment on the nature of small-scale run-of-river hydropower projects is helpful in order to provide a clear understanding of the extremely low impact of this type of investment. Small-scale run of river hydro power has a very low impact on river flow volume and all water diverted to the powerhouse is returned to the main stream. A very small ponding area occurs behind the low weir constructed across the river to facilitate the diversion of water into a channel. The volume of water accumulated behind the weir varies depending upon the site conditions but is typically less than five (5) minutes of the average waterflow of the river. It is also relevant to point out that small hydropower plants do not create any type of atmospheric, noise or other pollution and they cannot therefore have any negative impact on persons living in the close vicinity of these plants.

All four projects have secured the Environmental Clearance from the CEA and this report is available through the offices of EPL. Environmental Clearance for the Hapugastenne Phase I and Phase II projects was issued on October 25, 1999. Environmental Clearance for Hulu Ganga Phase I and II projects was issued on October 25, 2001.

These clearances reflect the finding that the environmental impact of the four projects is negligible. The general and specific conditions of approval of the EAs are in most instances generic, i.e., guidance on minimizing impacts of site preparation. Also, all projects require an environmental monitoring plan that covers surface water (not relevant in practice for run-of-river projects), flora and fauna within the river and below the diversion point, river bank erosion, and sediments upstream of the weir. The noteworthy conditions specific to each of the project sites are summarized below.

Hapugastenne Phases I and II



- To maintain the downstream in proper condition, a continuous uninterrupted flow of 50litres/sec shall be maintained by a suitable opening through the weir.

Hulu Ganga Phases I and II

To maintain the downstream in proper condition, a continuous uninterrupted flow of 50litres/sec shall be maintained by a suitable opening through the weirs of both phases.

SECTION E. Local stakeholder consultation

E.1. Solicitation of comments from local stakeholders

>>

The stakeholders for each of the four projects were identified as part of the process of seeking environmental clearance to proceed with the project. In all cases EPL has held meetings with the individuals living and working in the vicinity to explain the project's objectives and benefits. Due to the remote nature of the Hulu Ganga and Hapugastenne projects, there are very few local residents or structures. Those consultations allowed the developer to design the projects so that they did not/will not interfere with current land use and economic activity. In addition, as part of gaining the approval of the CEA, EPL has received approval (in writing) from the elected local government authority which represents the local community.

The villagers were informed of the project details and their comments were solicited at face to face meeting arranged with them. The meetings were arranged through the local government official called the Grama Niladhari (Village Officer) who is the focal point of all government interaction with villagers at this level. [A typical GN knows every single village household within his/her GN Division.] For each project we notified the GN of the basic parameters of the project and had him assemble a meeting between us and all villagers who could potentially be affected by the project in any way. Further meeting as necessary were arranged in the same manner during the construction of the projects.

The local representative was shown the minutes of the various meetings that were held with the stakeholders and all comments were recorded in these minutes.

EPL has found that there are usually a range of small issues connected with the operation of its hydropower plants which impact on the local communities in the vicinity of the plants which were unanticipated at the time prior to construction of the plants. These issues are typically addressed through an ongoing dialogue that EPL conducts with the local communities.

Further, EPL, in consultation with INCAF, prepared two documents, a Summary of Project Information and an Environmental Review Summary. These two documents together provided all salient details relating to the environmental and social aspect of the projects for which PDDs were prepared. These documents were translated into Sinhalese, the local language, and were made available for inspection by the public, including all stakeholders, for a period of one Month, starting on May 9, 2005. These documents were made available at Eco Power's head office and locally at the following addresses Hapugastenne Power House, Hapugastenne Rubber Estate, Gallella Alupola Power House, Alupola Estate, Alupola CECB Magal Ganga Project Office, Maliboda Estate, Nakkawita Hulu Ganga Sub Post Office, Hulu Ganga Town Divisional Secretariat, and Meegahakiula via Badulla

An advertisement was placed in a large Sinhalese language daily newspaper, the Lankadeepa, informing the public of the availability of the documents and soliciting comments. The comments could be sent to an IFC web site whose address was given in the advertisement or sent directly to the Chief Executive Officer of Eco Power. No comments were received during the one month period or thereafter to date.

**E.2. Summary of comments received**

>>

Comments received from local stakeholders are generally positive. Participants are eager to participate as employees of the project and are particularly enthusiastic regarding EPLs commitment to provide an annual Rs 200,000 (\$2,000) budget for the local community to use for community development projects of their choice.

E.3. Report on consideration of comments received

>>

As was stated in E.1., the stakeholder consultation process allowed EPL to map and take into account current land uses and economic activities in the final project design.

SECTION F. Approval and authorization

>> Host country approval dated 09/05/2005 has been obtained and was submitted for registration.

**Appendix 1: Contact information of project participants**

Organization	Eco Power (Private) Ltd
Street/P.O. Box	30/1 Bagatalle Road
Building	
City	
State/Region	Colombo
Postcode	3
Country	Sri Lanka
Telephone	++94(11) 4513470/1/2
Fax	+94(11) 4513470/1/2
E-mail	bhatiya@ecopower.lk
Website	Not applicable
Contact person	
Title	Chief Executive Officer
Salutation	Mr.
Last name	Bandaranaike Ranatunga
Middle name	
First name	Bhatiya
Department	Not applicable
Mobile	+94772244678
Direct fax	+94(11) 4513470/1/2
Direct tel.	+94(11) 4513470/1/2
Personal e-mail	bhatiya@ecopower.lk



Organization	IFC-Netherlands Carbon Facility (INCaF)
Street/P.O. Box	2121 Pennsylvania Avenue, NW
Building	
City	Washington
State/Region	District of Columbia
Postcode	20433
Country	USA
Telephone	+1 202-473-1368
Fax	+1 202-974-4404
E-mail	carbonfinance@ifc.org
Website	http://www.ifc.org/carbonfinance
Contact person	
Title	Program Manager, Carbon Finance
Salutation	Mr.
Last name	Widge
Middle name	
First name	Vikram
Department	
Mobile	
Direct fax	(202) 974-4404
Direct tel.	(202) 473-1368
Personal e-mail	



Appendix 2: Affirmation regarding public funding

The Hapugatenne and Hulu Ganga projects do not require public funding.

Appendix 3: Applicability of selected methodology

Described in Section B.2



Appendix 4: Further background information on ex ante calculation of emission reductions

Tables providing values obtained when applying formulae for Emission reduction Calculation in Section B.6.:

Step 1: Calculate the relative power contribution of each thermal power plant on the grid

Power plants		Date commissioned	Fuel source	Hours / year	Maintenance (days/yr) ^[a]	Forced outage rate (%) ^[a]	Operating hours	Capacity (MW) ^[a]	Annual Max. Energy (10 ⁹ kWh/yr) F = (D * E *1000)/10 ⁹	Contribution to total energy supply (% of kWh) G = F / (SUM: total thermal power available)
Variable Facilities as of August 2003				A	B	C	D	E		
<i>CEB-operated Kelanitissa Power Station</i>										
1	Gas turbines (old)	1980-82	Auto diesel	8760	40	20	6240	96	0.60	9.1%
2	Gas turbines (new)	1997	Auto diesel	8760	45	8	7066	115	0.81	12.4%
3	Kelanitissa steam power units	1962-63	Fuel oil	8760	40	20	6240	40	0.25	3.8%
<i>CEB-operated Sapugaskanda Power Station</i>										
4	Diesel plant	1984	Residual oil	8760	44	12	6780	72	0.49	7.4%
5	Diesel extension	1997-99	Residual oil	8760	44	20	6163	72	0.44	6.8%
6	Pielstick	2003	Fuel oil	8760	44	12	6780	22	0.15	2.3%
<i>Independent Power Producers (BOOT contracts)</i>										
7	Lakdhanavi diesel engine	1997	Auto diesel	8760	30	8	7397	22.5	0.17	2.5%
8	Asia Power Ltd diesel engine	1998	Auto diesel	8760	30	8	7397	51	0.38	5.8%
9	Colombo Power Ltd diesel engines	2000	Auto	8760	30	8	7397	64	0.47	7.2%



CDM – Executive Board

10	Matara diesel plant	2002	diesel Auto diesel	8760	30	8	7397	24.8	0.18	2.8%
11	Combined cycle plant 1 (JBIC-financed)	2002-03	Naptha Auto diesel	8760	32	5	7592	165	1.22	18.6%
12	Horana diesel plant	2003	diesel	8760	30	8	7397	24.8	0.18	2.8%
13	Combined cycle plant 2 (ADB guarantee)	2002	Fuel oil	8760	30	8	7397	163	1.21	18.4%
Capacity sub-total end 2003								932.1	6.59	100%

Step 2: Calculate the emissions factor for each thermal power plant.

Powerplants	Plant Conversi on efficiency	Heatrate	Carbon Content (unadjusted)	Combustion Efficiency	Carbon Content (adjusted)	Emissionsfactor	Emissionsfactor
	(%) ^[a]	(MJ/MWh)	(tC/TJ) ^[c]	Factor ^[d]	(tC/TJ) ^[c]	(kgC/MWh)	(kgCO ₂ /kWh)
		J=				N=J* M*	O= (N*44/12)/
	I	(1/I)*3.6*10 ³	K	L	M= K*L	10 ³ /10 ⁶	10 ³
FacilitiesasofAugust2003							
<i>CEB-operatedKelanitissaPowerStation</i>							
1 Gasturbines(old)	0.27	13155	20.2	0.99	20.0	263.1	0.9646
2 Gasturbines(new)	0.21	17419	20.2	0.99	20.0	348.4	1.2773
3 Kelanitissasteampowerunits	0.22	16024	20.2	0.99	20.0	320.4	1.1750
<i>CEB-operatedSapugaskandaPowerStation</i>							
4 Dieselplant	0.41	8733	21.1	0.99	20.9	183.3	0.6720
5 Diselextension	0.43	8314	21.1	0.99	20.9	173.7	0.6368
6 Pielstick	0.40	8955	20.2	0.99	20.0	179.1	0.6567



7	Lakdhanavidieselengine	0.40	9000	20.2	0.99	20.0	180.0	0.6599
8	AsiaPowerLtd dieselengine	0.40	9000	20.2	0.99	20.0	180.0	0.6599
9	ColomboPowerLtd dieselengines	0.40	9000	20.2	0.99	20.0	180.0	0.6599
10	Mataradieselplant	0.40	9000	20.2	0.99	20.0	180.0	0.6599
11	Combinedcycleplant1(JBIC-	0.30	12000	20.2	0.99	20.0	240.0	0.8799
12	Horanadieselplant	0.40	9000	20.2	0.99	20.0	180.0	0.6599
13	Combinedcycleplant2(ADBguarantee)	0.29	12414	20.2	0.99	20.0	248.3	0.9103

Step 3: Calculate the approximate operating margin of non-renewable plants connected to the grid

Power plants	Weighted average emissions (kgCO ₂ /kWh)) P = O * G	Approximate operating margin emissions (kgCO ₂ /kWh)) Q
--------------	--------------------------------------------------------------------------------	---------------------------------------------------------------------------------------

Facilities as of August 2003

CEB-operated Kelanitissa Power Station

1	Gas turbines (old)	0.0882
2	Gas turbines (new)	0.1584
3	Kelanitissa steam power units	0.0448

CEB-operated Sapugaskanda Power Station

4	Diesel plant	0.0501
5	Diesel extension	0.0431
6	Pielstick	0.0149

Independent Power Producers (BOOT contracts)

7	Lakdhanavi diesel engine	0.0168
8	Asia Power Ltd diesel engine	0.0397

**CDM – Executive Board**

	Colombo Power Ltd diesel	
9	engines	0.0477
10	Matara diesel plant	0.0185
	Combined cycle plant 1	
11	(JBIC-financed)	0.1639
	<i>Commissioned</i>	
12	Horana diesel plant	0.0185
	Combined cycle plant 2 (ADB	
13	guarantee)	0.1675

Approximate operating margin	0.8719
-------------------------------------	---------------

Step 4: Calculate the build margin

	Power plant	Date(s) commissioned	Annual Max. Energy (10⁹ kWh/yr)	Contribution to total energy supply (% of kWh)	Emissions factor (kg CO₂/kWh)	Weighted average emissions (kgCO₂/kWh) R
1	old laxapana	1950				
2	Kelanitissa steam power units	1962				
3	inginiyagala	1963				
4	wimalasurandra hydro	1965				
5	polpitiya	1969				
6	udawalawe	1969				
7	new laxapana	1974				
8	ukuwela	1976				
9	Kelanitissa old gas turbines	1980				
10	Bowatenna	1981				
11	Canyon hydro	1983				
12	Sapugaskanda old diesel	1984				
13	victoria	1985				
14	kotmale	1985				
15	randenigala	1986				
16	nilambe	1988				

**CDM – Executive Board**

17	Rantambe	1990				
18	Samanalawewa	1992				
19	Kelanitissa new gas turbines	1997				
20	Sapugaskanda new diesel ext. (4 units)	1997				
21	Lakdhanavi diesel engine	1997				
22	Asia Power Ltd diesel engine	1998				
23	Sapugaskanda new diesel ext. (4 units)	1999				
24	Colombo Power Ltd diesel engines	2000	0.47	0.14	0.66	0.0910
25	Matara diesel plant	2002	0.18	0.05%	0.66	0.0348
26	Pielstick Combined cycle plant 1 (JBIC-financed)	2003	0.15	0.04%	0.66	0.0289
27	Horana diesel plant	2002	1.22	0.36%	0.88	0.3148
28	Combined cycle plant 2 (ADB guarantee)	2003	0.18	0.05%	0.66	0.0348
29		2002	1.21	0.35%	0.91	0.3230
Capacity sub-total end 2003			3.41	100%		
Approximate build margin						0.8273



Step 5: Calculate the average emissions of the operating margin and the build margin:

Operating margin emissions	0.8719
Build margin emissions	0.8273

Average emissions (kgCO₂/kWh)	0.8496
-----------------------------------------------------	---------------

Table footnotes:

- [a] Figures are based on data in the CEB's expansion plan and the annual statistical digest for the years 1999 and 2002. Figures for independent operators are based on similar CEB-managed facilities.
- [b] Variables from World Bank GHG Handbook
- [c] Carbon content values taken from WB GHG Handbook except for fuel oil values taken from CEB own estimates. Both sources report their figures as derived from IPCC 1996 guidelines.

SUMMARY OF THE CEB EXPANSION PLAN METHODOLOGY

The CEB 2002-2016 expansion plan study identifies the expected future power generation investments using a systematic process, summarized below. First, the CEB prepares feasibility studies on several possible project candidates. The estimated capital costs of the various candidate projects are shown, below.

Table 1: Capital Cost Details of Expansion Candidates Considered

Plant	Capacity (MW)	PureConst.Cost (US\$/kW)		Total cost (US\$/kW)	Const Period (yrs)	IDC*at 10% of pure costs	Constcost incl. IDC (US\$/kW)		Economic life (yrs)
		Local	Foreign				Local	Foreign	
HYDRO POWER PROJECTCANDIDATES									
GinGanga	49	389.2	2095.2	2484.4	4	18.53	461.3	2483.5	50
Broadlands	40	523.9	2219.7	2743.6	4	18.53	621.0	2631.0	50
UmaOyaM	150	395.2	2001.0	2396.1	5	23.78	489.1	2476.7	50
oragolla	27	408.2	3123.2	3532.4	4	18.53	483.9	3701.9	50
THERMAL POWER PROJECT CANDIDATES									



Coal Trincomalee	300	147.2	844.2	991.4	4	18.53	174.5	1000.7	30
CoalWestCoast	300	237.2	770.7	1007.9	4	18.53	281.2	913.5	30
GasTurbine	35	62.0	488.5	550.6	1.5	6.51	66.1	520.3	20
GasTurbine	105	42.2	332.2	374.4	1.5	6.51	44.9	353.8	20
CombinedCycle (Kera)	150	155.7	680.5	836.3	3	13.54	175.6	767.4	30
Combinedcycle	300	113.9	474.8	588.6	3	13.54	129.3	539.0	30
Diesel-Fuel oil	10	110.0	1238.4	1348.4	2	8.79	119.6	1347.3	25
Diesel-Residual oil	10	110.0	1238.4	1348.4	2	8.79	119.6	1347.3	25
Steam –Fuel oil	150	177.4	825.9	1003.2	4	18.53	210.2	978.9	30
Steam –Fuel oil	300	150.0	698.1	848.0	4	18.53	177.7	827.4	30

* IDC = Interest During Construction.

For each of the candidate plants listed in the table, the CEB prepares estimates of fixed and variable operations and maintenance costs, establishes full load efficiencies, determines heat rates for thermal plants, etc. The result is an estimate, summarized in the following table, of the specific cost of generation of each of the candidate plants used in the expansion plan study.

Table 2: Specific Cost of Generation of Candidate Plants used in the 2002-2016 Expansion Plan

PROJECT/PLANT	CAPACITY (MW)	SPECIFIC COST (Jan2001borderprices)	
		USCts/kWh	Rs/kWh
HYDRO			



GinGanga	49	6.86	5.49
Broadlands	40	9.05	7.24
UmaOyaM	150	10.04	8.03
oragolla	27	10.27	8.22
THERMAL			
Coal Trincomalee(80% PF)	300	3.99	3.19
CoalWestCoast(80% PF)	300	4.13	3.31
CombinedCycle (60%PF)	300	5.70	4.56
CombinedcycleKera(60% PF)	150	5.80	4.62
Diesel-FuelOil(80% PF)	10	6.35	5.08
Diesel-Residual Oil(80%PF)	10	5.82	4.66
Steam-FuelOil(80%PF)	150	6.19	4.95
Steam – Fuel Oil (80% PF)	300	5.45	4.36
Gas Turbine(30%PF)	35	9.91	7.93
Gas Turbine(30%PF)	105	8.47	6.78

The CEB uses the System Simulation package (SYSIM) developed during the Master Plan Study in 1989 and the Energy and Power Evaluation Program (ENPEP), developed by the International Atomic Energy Agency (IAEA) to conduct expansion planning studies. The ELECTRIC module of ENPEP is used to determine the optimal generation expansion plan.

The following assumptions are applied to calculate the least-cost expansion plan:

- For the most recent study, the period of analysis is 2002-2021.
- All analyses were performed based on economic border prices for investments and operations.
- The exchange rate used is 80.04 Rs/US\$ (rate as of 1st January 2001).
- All costs are in constant January 2001 US Dollars.
- It is assumed that the power plants are commissioned at the beginning of each year.
- Capital costs are shown in two components, foreign cost and local cost.
- A conversion factor of 0.9 is applied to all local costs to obtain a border price equivalent.
- No taxes and duties are added to costs.
- Whenever results of project feasibility studies were available, these figures were adopted after adjustment to 2001 values.



- The fuel prices used are taken from World Bank price projections published in September
- 2001.
- The average loss to the economy due to electrical energy not supplied is estimated at 54.51

Rs/kWh or 0.68US\$/kWh (in 2001 prices). This figure comes from an evaluation published in 2000.

**Appendix 5: Further background information on monitoring plan****Project social benefit indicators**

ID number (project/date/ data type)	Data type	Data variable	Data unit	Measured (m), calculated (c) or estimated (e)	Recording frequency	Proportion of data to be monitored	How will the data be archived?	For how long is archived data to be kept?	Comment
H1-mmyy-E	Hapugastenne Phase I project employment benefits	Total short- and long-term employment benefits	Person-months	M	Annually	100%	Electronically and on paper	Two years after the last issuance of CERs for each project	
H2-mmyy-E	Hapugastenne Phase II project employment benefits	Total short- and long-term employment positions created	Person-months	M	Annually	100%	Electronically and on paper	Two years after the last issuance of CERs for each project	
HG1-mmyy-E	Hulu Ganga Phase II project employment benefits	Total short- and long-term employment positions created	Person-months	M	Annually	100%	Electronically and on paper	Two years after the last issuance of CERs for each project	
HG2-mmyy-E	Hulu Ganga Phase II project employment benefits	Total short- and long-term employment positions created	Person-months	M	Annually	100%	Electronically and on paper	Two years after the last issuance of CERs for each project	
H1-mmyy-P	Hapugastenne Phase I community development project financing	Project sponsor financial contributions to local development	Rupees	M	Annually	100%	Electronically and on paper	Two years after the last issuance of CERs for each project	



		projects							
H2-mmyy-P	Hapugastenne Phase II community development project financing	Project sponsor financial contributions to local development projects	Rupees	M	Annually	100%	Electronically and on paper	Two years after the last issuance of CERs for each project	
HG1-mmyy-P	Hulu Ganga Phase I community development project financing	Project sponsor financial contributions to local development projects	Rupees	M	Annually	100%	Electronically and on paper	Two years after the last issuance of CERs for each project	
HG2-mmyy-P	Hulu Ganga Phase II community development project financing	Project sponsor financial contributions to local development projects	Rupees	M	Annually	100%	Electronically and on paper	Two years after the last issuance of CERs for each project	

Appendix 6: Summary of post registration changes

1. In the registered PDD, the project was to be implemented for a total capacity of 13.15 MW. However, during the actual implementation, the capacity implemented was slightly different from what was registered. This is because while purchasing the equipment, the exact capacity turbines as mentioned in PDD was not available and thus the nearest capacity turbines were installed. The actual combined capacity of project is 13.568 MW with following break-up:

Power Plant	Capacity indicated in the registered PDD (MW)	Actual installed capacity (MW)
Hapugatenne I	4.8	5.052
Hapugastenne II	2.4	2.526
Hulu Ganga I	3.0	3.000
Hulu Ganga II	2.95	2.990
Total Capacity	13.15	13.568

2. The following has been changed from registered monitoring plan and is being submitted along with this monitoring plan:

In the registered PDD, the monitoring of electricity output from Hulu Ganga I and Hulu Ganga II were mentioned to be from separate meters. The Hulu Ganga Phase I and II plants are situated next to each other and are considered a single plant complex by the CEB. As a result the CEB only has a single meter to measure the combined electricity generation by the two plants each month.

Thus a single bi-directional meter is used to monitor the electricity output from Hulu Ganga I and Hulu Ganga II projects.

3. The following corrections have been done in the registered PDD:
 - a) Under Table 1, section A.4.3 and E.1.2.5: the estimated emission reductions were given as per the capacity of 13.15 MW. The revised PDD has included the actual capacity of the project activity and related emissions estimate.
 - b) Under section D.3 of the registered PDD: the sentence of “The specification of the meters will be as per the PPA” has been brought in to include reference to the specification of the meters used for measuring the electricity at the grid interconnection point.
 - c) The Annex 1 of the registered PDD has been corrected to reflect the actual details of the contact persons for the project activity as per the latest modalities of communication available in the project interface. Also, under section B.5.3 the details on the contact persons of the entity working out the baseline have been revised to reflect the actual contact details.
4. Under section E.1.2.1 of the registered PDD, the equations for calculating the emission reductions related to transportation and small engine related emissions were wrongly including the distance travelled and hours of operation. The same have been rectified as follows:

For transportation-related emissions:

Fuel for transportation x 2.68
(litres of fuel) (kg CO₂/litre)



For small engine-related emissions (cement mixer and generator):

Fuel for operation x 2.68
(litres) (kg CO₂/litre)

History of the document

Version	Date	Nature of revision
04.1	11 April 2012	Editorial revision to change history box by adding EB meeting and annex numbers in the Date column.
04.0	EB 66 13 March 2012	Revision required to ensure consistency with the "Guidelines for completing the project design document form for small-scale CDM project activities" (EB 66, Annex 9).
03	EB 28, Annex 34 15 December 2006	<ul style="list-style-type: none">The Board agreed to revise the CDM project design document for small-scale activities (CDM-SSC-PDD), taking into account CDM-PDD and CDM-NM.
02	EB 20, Annex 14 08 July 2005	<ul style="list-style-type: none">The Board agreed to revise the CDM SSC PDD to reflect guidance and clarifications provided by the Board since version 01 of this document.As a consequence, the guidelines for completing CDM SSC PDD have been revised accordingly to version 2. The latest version can be found at <http://cdm.unfccc.int/Reference/Documents>.
01	EB 07, Annex 05 21 January 2003	Initial adoption.
Decision Class: Regulatory Document Type: Form Business Function: Registration		